

CC-Light Installation and Setup Instructions

Software Installation from CD

- Insert CD into CD-ROM drive.
- Choose run from the Start menu.
- Type **d:\setup** (where *d* is the CD-ROM drive).
- Click OK or press Enter.
- Follow on-screen instructions.
- From the c drive double-click on the **CCLight** directory.
- Right click on **cclight.exe** and select Send To > Desktop (create shortcut)
- From the desktop double-click Lighthouse icon to launch program.

Software Installation from the Internet

- Click on the hyperlink at www.opktek.net / Technical Support / CCLight Setup Software. Either save the file to your computer or run it from the Internet.
- Go to the save location and double click he "**CCLightv1.00patch1**" icon and/or Follow the onscreen instructions.
- From the C drive double-click on the **CCLight** directory.
- Right click on **cclight.exe** and select Send To > Desktop (create shortcut)
- From the desktop double-click Lighthouse icon to launch program.

Single Channel Controller Setup

- From the **File** pull-down menu select **Options**.
- Setup **Light Control Configuration** as follows:
 - Config tab**
 - Number of light channels: 1
 - Light box serial port: Com (x)x=port connected to controller.
 - Settling time in programs: 0
 - CH 1 tab**
 - Minimum Light Level: 0
 - Maximum Light Level: 1000
 - Slider step size: 1
 - Channel Type: Single
 - Physical Channel: 1
 - Bitmap Filename: lc_1.bmp
 - Test Light Level: 0
 - Track Response: Checked
 - Disable At Minimum: Checked
- Click OK
- Close and restart program for changes to take effect.

Six Channel Controller Setup

- From the **File** pull-down menu select **Options**.
- Setup the **Light Control Configuration** as follows:
 - Config tab**
 - Number of light channels: 3
 - Light box serial port: Com (x)x=Port connected to controller.
 - Settling time in programs: 0
 - CH 1 tab**
 - Minimum Light Level: 0
 - Maximum Light Level: 1000
 - Slider step size: 1
 - Channel Type: Single
 - Physical Channel: 5
 - Bitmap Filename: lc_1.bmp
 - Test Light Level: 0
 - Track Response: Checked
 - Disable At Minimum: Checked

CH 2 tab

- Minimum Light Level: 0
- Maximum Light Level: 1000
- Slider step size: 1
- Channel Type: Single
- Physical Channel: 6
- Bitmap Filename: lc_2.bmp
- Test Light Level: 0
- Track Response: Checked
- Disable At Minimum: Checked

CH 3 tab

- Minimum Light Level: 0
- Maximum Light Level: 1000
- Slider step size: 1
- Channel Type: Quadrant
- Physical Channel: 0
- Bitmap Filename: Blank
- Test Light Level: 0
- Track Response: Checked
- Disable At Minimum: Checked

- Click OK

- Close and restart program for changes to take effect.